



PAR LED 1 x 60W COB (3 in 1)

Quickstart manual

1. Menu functions

Display	Range	Function
d001	001-512	DMX address setup 3 channels
A001	001-512	DMX address setup 7 channels
r255	000-255	Red
G255	000-255	Green
b255	000-255	Blue
F255	000-255	Strobe from value 010; (slow-fast)
CC15	00-15	Color snap change (slow-fast)
DE15	00-15	Color fade (slow-fast)
CP15	00-15	Color select
SoUd	/	Sound mode

2. DMX modes

3ch	Range	Function
1	000-255	Red
2	000-255	Green
3	000-255	Blue

7ch	Range	Function
1	000-255	Dimmer
2	000-255	Red
3	000-255	Green
4	000-255	Blue
5	000-004	Open
	005-255	Strobe (slow-fast)
6	000-050	DMX mode
	51-100	Color select
	101-150	Color snap
	151-200	Color fade
	201-250	Color pulse
	251-255	Sound mode
7	000-255	Functions speed (slow-fast)

3. Specification

Specification	
Power consumption	80 W
Supply voltage	110 - 240 V
Supply frequency	50 - 60 Hz
Diode type	RGB
Diode number	1
Diode power	60W
Display	LED
Control	4 buttons
Dimmer	Smooth 0-100%
DMX channels	3/7
Beam angle	40°
Control	DMX, Auto, Master/Slave, Sound
DMX IN	XLR
DMX OUT	XLR
Enclosure	ABS
Cooling	yes