



PAR LED 6x10W IP65

Quickstart Manual

1. Menu functions

Display	Ragne	Function
D001	000-512	8CH DMX setup
A001	000-512	4CH DMX setup
CC01	01-99	7 colors, snap change (slow to fast)
CP01	01-99	7 colors, smooth change (slow to fast)
DE01	01-99	7 colors, pulse change (slow to fast)
BE01	01-99	7 colors, sound activated change
FH01	01-99	Strobe speed (slow to fast)
R255	000-255	Red
G255	000-255	Green
DB255	000-255	Blue
O255	000-255	White

2. DMX modes

4ch	Range	Fucntion
1	000-255	Red
2	000-255	Green
3	000-255	Blue
4	000-255	White

8ch	Range	Fucntion
1	000-255	Dimmer
2	000-255	Strobe
3	000-050	DMX mode
	051-100	Color snap
	101-150	Color fade
	151-200	Color pulse
	201-255	no fucntion
4	000-255	Function speed (slow to fast)
5	000-255	Red
6	000-255	Green
7	000-255	Blue
8	000-255	White

3. Specification

Specification	
Power consumption	200W
Supply voltage	110 - 240 V
Supply frequency	50 - 60 Hz
Diode type	RGBW
Diode number	18
Diode power	10W
Display	LCD
Control	2 buttons
Dimming	Smooth 0-100%
DMX channels	4/8
Beam angle	25°
Control	DMX, Auto, Master/Slave, Sound
DMX IN	XLR
DMX OUT	XLR
Enclosure	Metal
IP protection	IP 65