



MINI LED MOVING HEAD 7 x 10 W

Quickstart manual

1. Menu functions

Display	Value	Function
<i>d001</i>	<i>ADD1-AS12</i>	DMX address setup
<i>MAFA</i>	<i>FASL</i>	Fast auto mode
	<i>MSLS</i>	Master sound mode
	<i>MSLC</i>	Master auto mode
	<i>SLRU</i>	Slave mode
	<i>MASL-SLOW</i>	Slow auto mode
<i>PAn</i>	<i>PAn</i>	PAN normal
	<i>rPAn</i>	PAN inverted
<i>TIL</i>	<i>TIL</i>	TILT normal
	<i>rTIL</i>	TILT inverted
<i>d15</i>	<i>d15</i>	Display normal
	<i>rd15</i>	Display reversed 180°
<i>14CH</i>	<i>14CH</i>	14ch mode
	<i>9CH</i>	9ch mode
<i>PA54</i>	<i>PA54</i>	PAN range 540°
	<i>PA36</i>	PAN range 360°
	<i>PA18</i>	PAN range 180°
<i>T127</i>	<i>T127</i>	TILT range 270°
	<i>T118</i>	TILT range 180°
	<i>T109</i>	TILT range 90°
<i>rEST</i>	<i>rEST</i>	Fixture reset
<i>LOAD</i>	<i>LOAD</i>	Load factory defaults

2. DMX modes

9CH	14CH	Range	Function
1	1	000-255	Pan
	2	000-255	Pan fine
2	3	000-255	Tilt
	4	000-255	Tilt fine
8	5	000-255	PT speed
3	6	000-007	no function
		007-134	Dimmer
		135-239	Strobe (slow-fast)
		240-255	Open
4	7	000-255	Red
5	8	000-255	Green
6	9	000-255	Blue
7	10	000-255	White
	11	000-007	DMX mode
		008-231	Color select
		232-255	Color snap
	12	000-255	Function speed
	13	000-007	No function
008-127		Auto mode	
128-255		Sound mode	
9	14	000-149	No function
		150-200	Reset
		201-255	No function

3. Specification

Specification	
Power consumption	80 W
Supply voltage	100 - 240 V
Supply frequency	50 - 60 Hz
Diode type	4in1
Diode number	7
Diode power	10 W
Display	LED
Control	4 buttons
Modes	DMX, Auto, Master/Slave, Sound
Beam angle	25°
Dimmer	Smooth 0-100%
DMX channels	9/14
Pan movement	540°
Tilt movement	180°
DMX mode	DMX512
DMX IN	XLR
DMX OUT	XLR
IP protection	IP20
enclosure	ABS
cooling	yes